

Instructions for using EZ Connectors with Flexible LED Strip

Please read carefully. Installing connectors improperly will damage your LED strips.

Do not peel back or remove paper backing



Note marking for correct cuts, line is between sets of electrical contact points. Cut only on these lines.



Open connector. Orient the connector so the red wire matches up to the +12V marking on the strip. For sideview strip, the red wire lines up on the side




Note flanges on connector. The cut strip end fits under these.



Strip end goes under flanges and under metal contacts. Contacts must rest on top of strip contact points.



If strip rides up over flange or contact, re-insert. Do not pry up metal contacts. This will cause an electrical arc and damage goods.



RGB strip has four contacts, one for each color, and one for +12V. Be sure all 4 metal contacts are on top of strip.



When strip is correctly inserted, close EZ connector lid over strip. Squeeze until lid clicks shut. Your strip is now ready to connect to power source. Repeated opening and closing of the connector will damage the end of the strip. If you have problems, you may have to make a new cut at the next set of cut marks. Questions? Contact us at sales@TheLEDLight.com or call 775-841-4490